


DIN W48×H24mm, Indication only, LCD pulse meter(RPM, RPS, Hz) [LR5N-B]

Specifications

Series		LR5N-B			
Appearances & Dimensions		 [W48×H24×L54mm]			
Input type		No-voltage input		Voltage input 1	Voltage input 2
Input signal level		● Impedance at short-circuit: Max. 10kΩ, residual voltage: Max. 0.5V ● Impedance at open-circuit: Min. 500kΩ		DC High voltage : 4.5-30VDC Low voltage : 0-2VDC AC Voltage : 3-30VAC	Voltage : 30-240VAC
Battery life cycle		Approx. over 3 years at 20°C (replaceable)			
Display method		LCD zero blanking type(Height : 8.7mm)			
Digit		5digit			
Display range	RPM	1 to 10000RPM			
	0.1RPM	0.1 to 1000.0RPM			
	RPS	1 to 1000RPS			
	Hz	1 to 1000Hz			
	0.1Hz	0.1 to 100.0Hz			
Display accuracy		F.S. ±0.1% ±1digit			
HOLD function		Included(External HOLD terminal)			
Insulation resistance		Min. 100MΩ(at 500VDC megger)			
Dielectric strength		2000VAC 50/60Hz for 1 minute(Cutoff current=10mA)			
Vibration	Mechanical	0.75mm amplitude at frequency of 10 to 55Hz(for 1 min.) in each of X, Y, Z directions for 1 hour			
	Malfunction	0.3mm amplitude at frequency of 10 to 55Hz(for 1 min.) in each of X, Y, Z directions for 10 minutes			
Shock	Mechanical	300m/s²(approx. 30G) in each of X, Y, Z directions for 3 times			
	Malfunction	100m/s²(approx. 10G) in each of X, Y, Z directions for 3 times			
Protection		IP66(Front panel only)			
Environ -ment	Ambient temperature	-10 to 50°C, storage : -25 to 65°C			
	Ambient humidity	35 to 85%RH, storage : 35 to 85%RH			
Unit weight		Approx. 58g			

※Environment resistance is rated at no freezing or condensation.

Connections



※Please use reliable contacts enough to flow 5μA of current when using input signal or reset signal as a contact.

※IN1 - No-voltage input

IN2 - Voltage input

• DC voltage input

• AC voltage input : Display AC frequency.

IN3 - AC voltage input : Display AC frequency.

※Choose one among IN1, IN2 and IN3 to use.

※Caution for IN3 input: If apply high voltage over 50VAC, it may cause an electric shock. Insulated transformer whose turn ratio is 1:1 must be installed, or countermeasures must be provided.

High-performance, Digital Pulse Meter [MP5S / MP5Y / MP5W / MP5M Series]

Ordering information

MP	5	S	-	4	N
					Output
					Power supply
					Size
					Digit
					Series
					MP
					5
					99999(5digit)
					M
					DIN W72×H72mm
					W
					DIN W96×H48mm
					Y
					DIN W72×H36mm
					S
					DIN W48×H48mm
					4
					100-240VAC 50/60Hz
					2
					24VDC(Only for MP5Y-24)
					2
					24VDC(Only for MP5Y-24)
					1
					Relay dual(High/Low-limit) output + NPN open collector output
					2
					Relay single(High-limit) output + NPN open collector output
					N
					Indicator
					M Type
					9
					PNP open collector quintuple output
					8
					NPN open collector quintuple output
					7
					PNP open collector quintuple output
					6
					NPN open collector quintuple output
					5
					PNP open collector quintuple output
					4
					NPN open collector quintuple output
					3
					PNP open collector quintuple output
					2
					NPN open collector quintuple output
					1
					Triple relay(H, GO, L)
					1
					Five relay(HH, H, GO, L, LL)
					A
					Indicator
					N
					Indicator
					N
					S Type
					Sub output(Display value output)
					—
					Indicator
					N
					Main output(Comparative value output)

※PNP open collector output : Option

Specifications (MP5S / MP5Y / MP5W Series)

Series	MP5S-4N	MP5Y-24	MP5Y-4□	MP5W-4□
Appearances & Dimensions	 [W48×H48×L90mm]	 [W72×H36×L102mm]		 [W96×H48×L100mm]
Display method	7 Segment LED display(Zero blanking type)			
Character size	W4 × H8mm	W6.8 × H13.8mm		
Max. indication	-19999 to 99999			
Power supply	100-240VAC 50/60Hz	24VDC	100-240VAC 50/60Hz	100-240VAC 50/60Hz
Allowable operation voltage	90 to 110%			
Power consumption	Max. 7.5VA	Max. 6W	Max. 7VA	Max. 6VA

Photo electric sensor
Fiber optic sensor
Door/Area sensor
Proximity sensor
Pressure sensor
Rotary encoder
Connector/Socket
Temp. controller
SSR/Power controller
Counter
Timer
Panel meter
Tacho/Speed/ Pulse meter
Display unit
Sensor controller
Switching mode power supply
Stepper motor& Driver&Controller
Graphic/ Logic panel
Field network device

■ Specifications (MP5S / MP5Y / MP5W Series)

Series		MP5S-4N	MP5Y-24	MP5Y-4□	MP5W-4□
Power for external sensor		12VDC ±10%, 80mA			
Input frequency		• Soild-state input : Max. 50kHz(Pulse width : Each over 10μs) • Contact input : Max. 45Hz(Pulse width : Over 11ms)			
Input level		[Voltage input] High : 4.5-24VDC, Low : 0-1.0VDC, Input impedance : 4.5kΩ [No-voltage input] Impedance at short-circuit : Max. 300Ω, Residual voltage : Max. 1V Impedance at open-circuit : Min. 100kΩ			
Measuring range		• Mode F1, F2, F7, F8, F9, F10 : 0.0005Hz to 50kHz • Mode F3 : 0.02s to 3,200s • Mode F4, F5, F6 : 0.01s to 3,200s • Mode F11, F12, F13 : 0 to 4 ×10 Count			
Measuring accuracy (23 ±5℃)		• Mode F1, F2, F7, F8, F9, F10 : F.S. ±0.05% rdg ±1digit • Mode F3, F4, F5, F6 : F.S. ±0.01% rdg ±1digit			
Display period		0.05 / 0.5 / 1 / 2 / 4 / 8sec.(It is same with period of output update.)			
Operation mode		Number of revolution/Speed/Frequency(F1), Passing speed(F2), Cycle(F3), Passing time(F4), Time width(F5), Time defference(F6), Absolute ratio(F7), Error ratio(F8), Density(F9), Error(F10), Length measurement(F11), Interval(F12), Multiplication(F13)			
Prescale function		Direct input method(0.0001×10 ⁻⁹ to 9.9999×10 ⁹)			
Hysteresis※ ¹		0 to 9999			
Other functions		• Lock setting function • Auto-Zero time setting function • Time unit selection function • Peak value monitoring function • Memory protection function (Mode F13 applied only)		• Lock setting function • Monitoring delay function • Auto-zero time setting function • Current output range selection(Current output type only) • Comparative output function(HH, H, GO, L, LL) • Time unit selection function • Deviation memory function(F output mode applied only) • Peak value monitoring function • Remote/Local switching function(Communication output type only) • Data bank switching function※ ² • Memory protection function(Mode F13 applied only)	
		Main output	Triple relay	—	250VAC 3A resistive load 3a
			Quintuple relay		
			NPN Open collector (Quintuple)		
Sub output	PNP Open collector (Quintuple)	12-24VDC 30mA Max.	12-24VDC 20mA max.		
	BCD Dynamic	—	NPN Open collector 12-24VDC 30mA Max.	NPN Open collector 12-24VDC 20mA max.	
	Low speed serial output	—	—		
	PV transmission	—	DC4-20mA Load 600Ω Max. (Response time : Max. 800ms)	DC4-20mA Load 600Ω Max.	
RS485 communication		—	31 channels, Mutual direction communication function		
Memory protection		Non-volatile memory(Input : Min. 100,000 times)			
Insulation resistance		Min. 100MΩ(at 500VDC megger) Between charge part and non-charge part			
Dielectric strength		2000VAC 60Hz 1minute(Between terminals of AC power and case, Between terminals of AC power and measuring input terminals)			
Impulse noise strength		±2000VAC R-phase, S-phase the square wave noise(pulse width : 1μs) by the noise simulator, repeat frequency 60Hz			
Vibration	Mechanical	0.75mm amplitude at frequency of 10 to 55Hz(for 1 min.) in each of X, Y, Z directions for 2 hour			
	Malfunction	0.5mm amplitude at frequency of 10 to 55Hz(for 1 min.) in each of X, Y, Z directions for 10 minutes			
Shock	Mechanical	300m/s ² (approx. 30G) in each of X, Y, Z directions for 3 times			
	Malfunction	100m/s ² (approx. 10G) in each of X, Y, Z directions for 3 times			
Relay life cycle	Malfunction	—	Min. 10,000,000 operations		
	Mechanical	—	Min. 100,000 operations(250VAC 3A load current)		
Environ-ment	Ambient temperature	-10 to 50℃, storage : -20 to 60℃			
	Ambient humidity	35 to 85%RH, storage : 35 to 85%RH			
Approval		  	—	  	  
Weight ※ ³		Approx. 199.5g (approx. 141.5g)	Approx. 209g(approx. 117g)		Approx. 301.5g (approx. 177g)

※1: The hysteresis setting range is changed by the setting position of decimal point.


※2: Data bank switching function is in MP5W Series only.

※3: The weight with packaging and the weight in parentheses is only unit weight.

■ Connections


◎ MP5S Series

● MP5S-4N(Indicator)




◎ MP5Y Series

● MP5Y-□N(Indicator)



● MP5Y-□4 to □5(Main/Sub output type)




※1: It is used for RESET terminal when an operation mode is F13.

● Main output(Connector)


● MP5Y-□1(NPN open collector output)

MAIN OUT
(NPN OPEN COLLECTOR:12-24VDC Max. 30mA)



● MP5Y-□2(PNP open collector output)

MAIN OUT
(PNP OPEN COLLECTOR:12-24VDC Max. 30mA)




※Main output type & sub output type : Customizable

● Sub output(Connector)


● MP5Y-□3(BCD dynamic output)

BCD OUT
(NPN OPEN COLLECTOR:12-24VDC Max. 30mA)




● MP5Y-□4(PV transmission output)

DC4-20mA
Load 600Ω Max.




● MP5Y-□5(RS485 communication output)

RS485 B(-)




◎ MP5W Series


● MP5W-□N(Indicator)




● MP5W-□A(Five relay output)




● MP5W-□1(Triple relay output)



● Main output+Sub output(Connector)



● MP5W-□2/ MP5W-□3(NPN/PNP open collector output + BCD output)



● MP5W-□4/ MP5W-□5(NPN/PNP open collector output + PV transmission output(DC4-20mA) output)




Photo electric sensor

Fiber optic sensor

Door/Area sensor

Proximity sensor

Pressure sensor

Rotary encoder

Connector/Socket

Temp. controller

SSR/Power controller

Counter

Timer

Panel meter

Tacho/Speed/ Pulse meter

Display unit

Sensor controller


Switching mode power supply

Stepper motor & Driver&Controller


Graphic/Logic panel

Field network device

● **MP5W-□6/ MP5W-□7**(NPN/PNP open collector output + Low speed serial output)




● **MP5W-□8/ MP5W-□9**(NPN/PNP open collector output + RS485 communication output)




◎ **MP5M Series**

● **MP5M-4N**(Indicator)



● **MP5M-41**(High-limit setting type)



● **MP5M-42**(High/Low-limit setting type)

